

Theory of $\omega^{-4/3}$ law of the power spectrum in dissipative flows

Hisao Hayakawa

Department of Physics, Yoshida-South Campus, Kyoto University, Kyoto 606-8501, Japan

Abstract

It is demonstrated that $\omega^{-4/3}$ law of the power spectrum with the angular frequency ω in dissipative flows is produced by the emission of dispersive waves from the antikink of an congested domain. The analytic theory predicts the spectrum is proportional to ω^{-2} for relatively low frequency and $\omega^{-4/3}$ for high frequency.

05.40.-a,45.70.Mg 05.60.-k

Recently, much attention has been attracted to collective dynamics of dissipative particles [1,2]. In particular, physics of granular flows [3–6] and traffic flows [7,8] are developing subjects. In such dissipative flows, we often observe the coexistence of congested regions and dilute regions. It is important to know the mechanism of the emergence of congestion of traffic and granular flows. Although we have some exact results on the formation of congested domains in one-dimensional traffic flow [9,10], we still do not understand the details of the fluctuation of dissipative flows.

In experiments of dissipative flows, we usually measure the power spectrum which is the Fourier transform of the auto-correlation function. It is known that traffic flows and granular flows in a pipe have the power spectra obeying $\omega^{-\beta}$ law with the angular frequency ω [11,12]. Several years ago, Moriyama *et al.* [13] have confirmed that granular flow in a pipe should have the spectrum with $\beta = 4/3$. We also expect that the power spectrum obeying $\omega^{-4/3}$ law is universal for dissipative flows in the coexistence of congested-flow and sparse-flow. [3,13–16] This law is robust in the experiments of granular flows, which can be observed without tuning of a suitable set of parameters. [13,16]

Although the previous papers [3,13] proposed the mechanism of $\omega^{-4/3}$ law, their derivation might be incomplete. We can list several defects in their derivation: (i) They assumed that the system is in a weakly stable region of homogeneous state. However, $\omega^{-4/3}$ can be commonly observed in the case of the coexistence between congestion and the sparse-flow. The power exponent β is drastically small when there are no definite domains in systems. [15,16] (ii) The experiments [13,16] suggest that $\omega^{-4/3}$ law is robust without fine-tuning when phase separations take place, but the theory assumes that the system is in the vicinity of the neutral curve of the linear stability analysis. (iii) The theoretical spectrum depends on the wave number but there is no wave-number dependence in the actual observation in experiments. [3,13] (iv) Although the theory assumes that the relaxation process of internal structures, it is not clear what the relevant relaxation process is. Therefore, one is skeptical of the validity of the previous theory to explain $\omega^{-4/3}$ law.

Recently, Takesue *et al.* [17] have solved a kink-diffusion problem in the totally asym-

metric simple exclusion process (TASEP) [18] and derived $\omega^{-3/2}$ law of the power spectrum. Although TASEP contains only a kink which connects one congested domain with a dilute region, their analysis is suggestive to understand more realistic situations in traffic and granular flows. In this Communication, we thus try to re-derive $\omega^{-4/3}$ law in the case of coexistence between congestion and sparse-flow.

In order to proceed the analysis we should recall that all of one-dimensional models for traffic and granular flows in weakly unstable regions can be described by trains of quasi-solitons stabilized by small dissipations. [3,19–21] In general, a dilute region is connected with a congested region by asymmetric interfaces [3,20,21] which may be characterized by the soliton equation. [19] We call a front interface the kink and a backward interface the antikink. The antikink is not stable in the actual situations and emits dispersive waves backward. The waves are caught by the next domain. In the simplest situation, we can ignore the widths of the kinks and antikinks which may be much smaller than the typical domain size.

From the observation of experiments the power spectrum may not be related to the formation process of domains but be characterized by the emission of dispersive waves from an antikink. Thus, we ignore the formation of a congested domain but focus on the decay process of the domain. We also map the model onto a one-dimensional space, where the position fixed in an experimental system is denoted by x and the system size is L and the boundaries are located at $x = \pm L/2$. For simplicity, we place a detector to measure the power spectrum at $x = 0$, *i.e.* the center of the system. Let us introduce the packing fraction $\phi(x, t) \equiv n(x, t)/n_0$ where n_0 is the maximum density.

If we assume that an idealistic congested domain exists in the system at time $t = 0$, the packing fraction is given by $\phi(x, t = 0) = 1$ between $x = x_0$ and $x = x_0 + l$, and $\phi(x, 0) = 0$ for otherwise, where l and x_0 are the size of the domain and the position of an antikink at $t = 0$, respectively. The equivalent expression is

$$\phi(x, 0) = \frac{l}{L} + \sum_{n=1}^{\infty} \frac{\cos \frac{2n\pi x}{L}}{n\pi} \left\{ \sin \frac{2n\pi(x_0 + l)}{L} - \sin \frac{2n\pi x_0}{L} \right\}$$

$$-\sum_{n=1}^{\infty} \frac{\sin \frac{2n\pi x}{L}}{n\pi} \left\{ \cos \frac{2n\pi(x_0 + l)}{L} - \cos \frac{2n\pi x_0}{L} \right\}. \quad (1)$$

On the other hand, the antikink is unstable because of the dispersion of propagating velocity, though we can ignore such the effect for the kink. Thus, we assume that the time dependence of $\phi(0, t)$ can be described by

$$\phi(0, t) = \frac{l}{L} + \sum_{n=1}^{\infty} \frac{1}{n\pi} \left\{ \sin \frac{2n\pi(x_0 + l + c_0 t)}{L} - \sin \frac{2n\pi(x_0 + c_0 t(1 - (\frac{2n\pi\xi}{L})^2))}{L} \right\}, \quad (2)$$

where c_0 is the average speed of domains and ξ is a characteristic length scale of the dispersion relation. We note that the shape of domain at time t is no longer idealistic one but is decayed.

With the aid of Wiener-Khinchin theorem, the power spectrum $I(\omega)$ and the auto-correlation function $C(t)$ can be written as

$$I(\omega) \equiv \frac{1}{\sqrt{2\pi}} \int_{-\infty}^{\infty} dt e^{i\omega t} C(t), \quad C(t) \equiv \langle \phi(0, 0) \phi(0, t) \rangle, \quad (3)$$

where the ensemble average in eq.(3) is interpreted as the average by the position of the antikink x_0 . Because the domain propagates with the constant speed c_0 if we neglect the dispersion, the existence probability of domains should be uniform except for the boundary regions. Thus, we may assume the probability distribution function $P(x_0) = 1/L$ and $C(t) = \frac{1}{L} \int_{-L/2}^{L/2} dx_0 \phi(0, 0) \phi(0, t)$. Substituting eqs.(1) and (2) into (3) we obtain

$$C(t) = \frac{l^2}{L^2} + J_0(t) + J_1(t) + J_2(t), \quad (4)$$

where

$$J_0(t) = \sum_{n=1}^{\infty} \frac{1}{2\pi^2 n^2} \left\{ \cos \frac{2\pi n c_0 t}{L} - \cos \frac{2\pi n}{L} (l + c_0 t) \right\} \quad (5)$$

$$J_1(t) = -\sum_{n=1}^{\infty} \frac{1}{2n^2 \pi^2} \left\{ 1 - \cos \left[\frac{2\pi n}{L} c_0 t \right] \cos \left[\left(\frac{2\pi n}{L} \right)^3 \xi^2 c_0 t \right] - \sin \left[\frac{2\pi n}{L} c_0 t \right] \sin \left[\left(\frac{2\pi n}{L} \right)^3 \xi^2 c_0 t \right] \right\} \quad (6)$$

$$J_2(t) = \sum_{n=1}^{\infty} \frac{1}{2n^2 \pi^2} \left\{ 1 - \cos \left[\frac{2\pi n}{L} (l - c_0 t) \right] \cos \left[\left(\frac{2\pi n}{L} \right)^3 \xi^2 c_0 t \right] + \sin \left[\frac{2\pi n}{L} (l - c_0 t) \right] \sin \left[\left(\frac{2\pi n}{L} \right)^3 \xi^2 c_0 t \right] \right\}. \quad (7)$$

Here, $J_0(t)$ in eq.(4) can be calculated as

$$J_0(t) = \frac{l}{2L}(1 - \frac{l}{L}) - \frac{lc_0t}{L^2}, \quad (8)$$

where we use the formula $\sum_{n=1}^{\infty} \cos nx/n^2 = \pi^2/6 - \pi x/2 + x^2/4$. Thus, $I_0(\omega) \equiv \frac{1}{\sqrt{2\pi}} \int_{-\infty}^{\infty} dt e^{i\omega t} (l^2/L^2 + J_0(t))$ becomes

$$I_0(\omega) = \sqrt{2\pi} \frac{l(L+l)}{2L^2} \delta(\omega) + \sqrt{\frac{2}{\pi}} \frac{lc_0}{L^2} \omega^{-2}. \quad (9)$$

The evaluations of $J_1(t)$ and $J_2(t)$ are nontrivial. When we assume $c_0t \ll L$ the summation in $J_1(t)$ can be replaced by the integral. From the expansion by c_0t/ξ we obtain

$$\begin{aligned} J_1(t) &\simeq -\frac{1}{3\pi L} (\xi^2 c_0t)^{1/3} \left[\int_0^{\infty} dz \frac{1 - \cos z}{z^{4/3}} - \left(\frac{c_0t}{\xi} \right)^{2/3} \int_0^{\infty} dz \frac{\sin z}{z} \right] \\ &= -\frac{1}{3L\Gamma(4/3)} (\xi^2 c_0t)^{1/3} + \frac{c_0t}{6L}, \end{aligned} \quad (10)$$

where we use $\int_0^{\infty} dz (1 - \cos z)/z^{4/3} = \pi/\Gamma(4/3)$ and $\int_0^{\infty} dz \sin z/z = \pi/2$ with the Gamma function $\Gamma(z)$. The corresponding Fourier transform of $J_1(t)$ is thus given by

$$I_1(\omega) = \frac{\sqrt{2}}{6\sqrt{\pi}L} (\xi^2 c_0)^{1/3} \omega^{-4/3} - \frac{\sqrt{2}c_0}{6\sqrt{\pi}L} \omega^{-2}. \quad (11)$$

On the other hand, for $l \gg c_0t$, $J_2(t)$ can be evaluated as

$$\begin{aligned} J_2(t) &\simeq \sum_{n=1}^{\infty} \frac{1}{2\pi^2 n^2} \left\{ 1 - \cos \frac{2\pi n l}{L} \cos \left(\frac{2\pi n}{L} \right)^3 \xi^2 c_0t + \sin \frac{2\pi n l}{L} \sin \left(\frac{2\pi n}{L} \right)^3 \xi^2 c_0t \right. \\ &\quad \left. - \frac{2\pi n}{L} c_0t \cos \frac{2\pi n l}{L} \sin \left[\left(\frac{2\pi n}{L} \right)^3 \xi^2 c_0t \right] \right\} \\ &\simeq \frac{l}{\pi L} J_{21}(t) - \frac{c_0t}{\pi L} J_{22}(t). \end{aligned} \quad (12)$$

Here $J_{21}(t)$ and $J_{22}(t)$ are respectively given by [22]

$$\begin{aligned} J_{21}(t) &\equiv \int_0^{\infty} dx \frac{1}{x^2} (1 - \cos x \cos[x^3 bt] + \sin x \sin[x^3 bt]) \\ &= \frac{1}{720} [-120\sqrt{3}(bt)^{1/3} \Gamma(-1/3)_1 F_4[-\frac{1}{6}; \frac{1}{6}, \frac{1}{2}, \frac{2}{3}, \frac{5}{6}; \frac{1}{11664(bt)^2}] \\ &\quad + 60\sqrt{3}(bt)^{-1/3} \Gamma(1/3)_1 F_4[\frac{1}{6}; \frac{1}{2}, \frac{5}{6}, \frac{7}{6}, \frac{4}{3}; \frac{1}{11664(bt)^2}] \\ &\quad + \{120\pi - 20\sqrt{3}(bt)^{-2/3} \Gamma(2/3)_1 F_4[\frac{1}{3}; \frac{2}{3}, \frac{7}{6}, \frac{4}{3}, \frac{3}{2}; \frac{1}{11664(bt)^2}] \\ &\quad + \sqrt{3}(bt)^{-4/3} \Gamma(4/3)_1 F_4[\frac{2}{3}; \frac{4}{3}, \frac{3}{2}, \frac{5}{3}, \frac{11}{6}; \frac{1}{11664(bt)^2}]\} \end{aligned} \quad (13)$$

with $b \equiv \xi^2 c_0 / l^3$, and

$$\begin{aligned}
J_{22}(t) &\equiv \int_0^\infty dx \frac{\cos x \sin[x^3 bt]}{x} \\
&= \frac{1}{216(bt)^{4/3}} [-18\sqrt{3}\Gamma(2/3)(bt)^{2/3} {}_1F_4[\frac{1}{3}; \frac{1}{2}, \frac{2}{3}, \frac{7}{6}, \frac{4}{3}; \frac{1}{11664(bt)^2}] \\
&\quad + \pi\{36(bt)^{4/3} + \frac{1}{\Gamma(4/3)} {}_1F_4[\frac{2}{3}; \frac{5}{6}, \frac{4}{3}, \frac{3}{2}, \frac{5}{3}; \frac{1}{11664(bt)^2}]\}, \tag{14}
\end{aligned}$$

where ${}_1F_4[a_1; b_1, b_2, b_3, b_4; z] \equiv \sum_{k=0}^\infty (a_1)_k z^k / [(b_1)_k \cdots (b_4)_k k!]$ with $(\alpha)_k = \alpha(\alpha+1)\cdots(\alpha+k-1)$ is the generalized hypergeometric function.

The expressions of $J_{21}(t)$ and $J_{22}(t)$ are complicated. For example, the Fourier transforms of $J_{21}(t)$ is given by [22]

$$\begin{aligned}
I_{21}(\omega) &= -\frac{\sqrt{\pi/2}}{360b^{4/3}\omega^{4/3}} (120b^{5/3} {}_0F_5[; \frac{1}{6}, \frac{1}{3}, \frac{1}{2}, \frac{2}{3}, \frac{5}{6}; -\frac{\omega^2}{46656b^2}] \\
&\quad - 60b\omega^{2/3} {}_0F_5[; \frac{1}{2}, \frac{2}{3}, \frac{5}{6}, \frac{7}{6}, \frac{4}{3}; -\frac{\omega^2}{46656b^2}] \\
&\quad + 20\sqrt{3}b^{2/3}\omega {}_0F_5[; \frac{2}{3}, \frac{5}{6}, \frac{7}{6}, \frac{4}{3}, \frac{3}{2}; -\frac{\omega^2}{46656b^2}] \\
&\quad - 10b^{1/3}\omega^{4/3} {}_0F_5[; \frac{5}{6}, \frac{7}{6}, \frac{4}{3}, \frac{3}{2}, \frac{5}{3}; -\frac{\omega^2}{46656b^2}] \\
&\quad + \sqrt{3}\omega^{5/3} {}_0F_5[; \frac{7}{6}, \frac{4}{3}, \frac{3}{2}, \frac{5}{3}, \frac{11}{6}; -\frac{\omega^2}{46656b^2}]). \tag{15}
\end{aligned}$$

It should be noted that the Fourier transform of $J_{22}(t)$ becomes complex. This is because the expression we obtain depends on the initial condition and the choice of the frame. If the system is Galilei invariant, such the term should be zero. Therefore, we regard the contribution from $J_{22}(t)$ as unimportant.

In the limit of $\omega \rightarrow 0$, $I_2(\omega)$ becomes

$$I_2(\omega) \simeq \frac{l}{\pi L} I_{21}(\omega) \rightarrow -\frac{\sqrt{2}}{6\sqrt{\pi}L} (\xi^2 c_0)^{1/3} \omega^{-4/3}. \tag{16}$$

It is notable that this asymptotic expression of $I_2(\omega)$ is canceled with the term proportional to $\omega^{-4/3}$ in $I_1(\omega)$. That is, the spectrum obeying $\omega^{-4/3}$ disappears and $I(\omega) \sim \omega^{-2}$ in the limit of $\omega \rightarrow 0$.

On the other hand, though $I_{21}(\omega)$ is singular in the limit of $\omega \rightarrow \infty$, $I_{21}(\omega)$ is regular for enough large ω . In fact, one can obtain the analytic expansion of $J_{21}(t)$ near $bt = 0.001$ as

$2J_{21}(t)/\pi \simeq 1 + \alpha(bt - 0.001) + O((bt - 0.001)^2) \simeq 1 + \alpha bt + \dots$ with $\alpha = 0.000229538$. If we replace $J_{21}(t)$ by this approximate function, we obtain the approximate Fourier transform

$$I_{21}(\omega) \sim \frac{\pi^{3/2}}{\sqrt{2}}\delta(\omega) - \sqrt{\frac{\pi}{2}}\alpha b\omega^{-2} \quad (17)$$

for large ω .

Thus, we obtain the power spectrum $I(\omega) = I_0(\omega) + I_1(\omega) + I_2(\omega)$ as

$$I(\omega) = \frac{\sqrt{2}}{6\sqrt{\pi}L}(\xi^2 c_0)^{1/3}\omega^{-4/3} - \frac{\sqrt{2}c_0}{6\sqrt{\pi}L}(1 - \frac{6l}{L})\omega^{-2} + \frac{l}{\pi L}I_{21}(\omega) \quad (18)$$

for $\omega \neq 0$. For large ω , $I(\omega)$ is dominated by the term proportional to $\omega^{-4/3}$ as

$$I(\omega) \rightarrow \frac{\sqrt{2}}{6\sqrt{\pi}L}(\xi^2 c_0)^{1/3}\omega^{-4/3}. \quad (19)$$

Thus, we derive the spectrum obeying $\omega^{-4/3}$. Figure 2 shows the comparison of eq.(18) with eq.(19), where we can see the tail obeying $\omega^{-4/3}$ for large ω , while eq.(18) seems to obey ω^{-2} for small ω . It is obvious that both expressions (18) and (19) become identical for larger ω .

It should be noted that the actual process includes many other factors for larger ω and smaller ω . In experiments, $I(\omega)$ decays exponentially for larger ω , because the initial state is not in an idealistic domain as we have assumed here. To reproduce the full shape of spectrum we need to contain the formation process of domains for our analysis. That is an important future problem to be solved. Nevertheless, we believe that our picture presented here captures the essence of physics and clarify the mechanism of emergence of $\omega^{-4/3}$ law.

In this Communication, we have demonstrated that the main process to produce $\omega^{-4/3}$ law is the emission of the dispersive wave from an antikink. This result is universal when isolated congested domains exist in a dissipative flow. Through the analysis, we have revised the previous uncertain picture.

The author thanks Namiko Mitarai for fruitful discussion. This study is partially supported by the Grants-in-Aid of Japan Space Forum, and Ministry of Education, Culture, Sports, Science and Technology (MEXT), Japan (Grant No. 15540393) and the Grant-in-Aid for the 21st century COE "Center for Diversity and Universality in Physics" from MEXT, Japan.

REFERENCES

- [1] H. M. Jaeger, S. R. Nagel and R. P. Behringer, *Rev. Mod. Phys.* **68**, 1259 (1996).
- [2] I. Goldhirsch, *Ann. Rev. Fluid Mech.* **35**, 267 (2003).
- [3] H. Hayakawa and K. Nakanishi, *Prog. Theor. Phys. Supp.* **130**, 57 (1998).
- [4] O. Pouliquen, *Phys. Fluids*, **11**, 542 (1999).
- [5] N. Mitarai, H. Hayakawa, and H. Nakanishi, *Phys. Rev. Lett.* **88**, 174301 (2002).
- [6] N. Mitarai and H. Nakanishi, *J. Fluid Mech.* **507**, 309 (2004).
- [7] D. Helbing, *Rev. Mod. Phys.* **73**, 1067 (2001).
- [8] M. Fukui, Y. Sugiyama, M. Schreckenberg and D. E. Wolf eds. *Traffic and Granular Flow'01* (Springer, Berlin, 2003).
- [9] Y. Igarashi, K. Itoh and K. Nakanishi, *J. Phys. Soc. Jpn.* **68**, 791 (1999).
- [10] Y. Igarashi, K. Itoh, K. Nakanishi, K. Ogura and K. Yokokayawa, *Phys. Rev. Lett.* **85**, 718 (1999).
- [11] S. Horikawa, A. Nakahara, T. Nakayama, and M. Matsushita, *J. Phys. Soc. Jpn.* **64**, 1870 (1995).
- [12] T. Musha and H. Higuchi, *Jpn. J. Appl. Phys.* **15**, 1271 (1976).
- [13] O. Moriyama, N. Kuroiwa, M. Matsushita and H. Hayakawa, *Phys. Rev. Lett.* **80**, 2833 (1998).
- [14] G. Peng and H. J. Herrmann, *Phys. Rev. E* **49**, R1796 (1994), *ibid* **51**, 1745 (1995).
- [15] Y. Yamazaki, S. Tateda, A. Awazu, T. Arai, O. Moriyama and M. Matsushita, *J. Phys. Soc. Jpn.* **71**, 2859 (2002).
- [16] O. Moriyama, N. Kuroiwa, S. Tateda, T. Arai, A. Awazu, Y. Yamazaki, and M. Mat-

- sushita, Prog. Theor. Phys. Suppl. **150**, 136 (2003).
- [17] S. Takesue, T. Mitsudo and H. Hayakawa, Phys. Rev. E **68**, 015103 (R) (2003).
- [18] G. M. Schütz, Exactly Solvable Models for Many-Body Systems Far From Equilibrium, in Phase Transitions and Critical Phenomena Vol. 19 edited by C. Domb and J. L. Lebowitz (Academic, London, 2001).
- [19] T. S. Komatsu and S. Sasa, Phys. Rev. E **52**, 5574 (1995).
- [20] H. Hayakawa and K. Nakanishi, Phys. Rev. E **57**, 3839 (1998).
- [21] S. Wada and H. Hayakawa, J. Phys. Soc. Jpn. **67**, 763 (1998).
- [22] We have used MATHEMATICA for the calculation.




FIG. 1. A schematic picture of the propagation of a domain (its size l) with the speed c_0 . The dispersive wave emits from the antikink interface at x_0 .




FIG. 2. Log-log plots of eqs.(18) and (19) as the frequency spectra. We adopt the parameters $l/L = \xi/L = 0.3$ and $Lb/c_0 = L/l = 10/3$.